

## Generating Set

### GI 2000 SX Inverter (2 x 13A) - Petrol

#### Key Features

- Honda GX petrol engine
- Engine shut down for low oil level
- Inverter power
- Automatic voltage regulator "AVR"
- Sockets: 2 x 230V 13A
- Overload warning light
- Battery charger 12V
- 10 hour fuel tank
- Portable
- EC noise compliant



#### A.C. Generation - 50Hz - Single Phase, Brushless Alternator

Stand-by single-phase power *	1.7 kVA (1.7 kW) / 230V / 7.4A
PRP single-phase power *	1.5 kVA / 230V / 6.5A
Power factor (cos)	1
Battery charger	12V c.c. / 8.3A
Insulation class	H

On request other voltages and frequencies (60Hz)

\* Output power according to ISO 8528-1

#### Engine - Petrol, 4-Stroke, OHV, Air Cooled

Model	Honda GX 100
Output *	2.3 kW (3.1 HP)
Cylinders / Displacement	954cm <sup>3</sup>
Speed	4500 rpm
Fuel consumption (75% of PRP)	0.75 l/h

\* Maximum output (not overloadable) according to ISO 3046/1

#### General Specifications

Tank capacity	7.7 litres
Running time (75% Load)	10 hours
IP protection degree	IP 23
Dimensions LxWxH (mm) *	560 x 340 x 415
Dry weight *	22 Kg
Noise level @ 7 metres	93 LwA 68 dB(A)

\* Dimensions and weight (Kg) are inclusive of all parts without wheels and towbar

#### Optional

- Earthing kit
- Trolley CTM7/1 (4 wheels D 100mm)
- Trolley CTM7/3 (2 foldable handles and 2 wheels)
- Carrying kit TRM7 (4 folding handles)



Petrol Engine



Air Cooling



Manual Recoil



Engine Shut Down (Oil)



Permanent Magnet Alternator



2 x 13A Plug Sockets



Thermal Shut Off



Battery Charger



Automatic Voltage Reg.

Order Code: 35.35102